



IPM-ADC

Analog to Digital IPack Module
16-bit A/D with 16 differential lines

FEATURES

- ▶ 16-bit A/D converter
- ▶ 2048 word FIFO
- ▶ 32 bit 1us resolution timetag
- ▶ On-board IRIG-B decoder
- ▶ 4us conversion time (250 kS/s)
- ▶ 16 differential or 32 single-ended inputs
- ▶ Available input voltages:
 $\pm 2.5V$, $\pm 5V$, $\pm 10V$, 0-2.5V, 0-5V,
and 0-10V ranges
- ▶ Programmable scan control
- ▶ Four scanning modes
- ▶ User-programmable interval timer
- ▶ External trigger input and output
- ▶ Programmable gain for individual channels
- ▶ Post-conversion interrupts
- ▶ Available in extended temperature
- ▶ Programmable data format (binary 2's complement, straight binary)

OVERVIEW

The IPM-ADC provides a fast 16-bit resolution Analog to Digital (A/D) conversion. Available as a 32 MHz single-size Industry Pack (IPack) module, the IPM-ADC offers programmable scan control and up to four scanning modes.

The user can scan all channels or define a subset for more frequent sampling. Burst mode scans selected channels at the maximum conversion rate. Uniform mode performs conversions at user-defined intervals. Both modes can scan continuously, or execute a single cycle upon receiving a trigger. Analog samples and timetags are accessible through a 2048 word FIFO.

The IPM-ADC includes on-board IRIG-B decoder and sampling timetags providing accurate timing and synchronization between channels and modules.

CARRIER BOARD SUPPORT

The functionality of the IPM-ADC is further enhanced by the power of MAX Technologies' line of intelligent multi-platform (VME, PCI, CPCI, PXI) carrier boards. All modules and carrier boards are synchronized and time correlated to 32-bit microsecond-resolution.

SOFTWARE SUPPORT

A simple ANSI-C library is available to control the module on a carrier board. This low-level library can be adapted easily to any RTOS with little or no modification.

Also the MX-Foundation library provides high-level abstraction of hardware and allows to easily control mixed protocols and I/O modules on one or multiple carrier boards.

SOFTWARE

- ▶ MX-Foundation multi-protocol software API available for Windows and Linux and IRIX
- ▶ Portable Low-Level ANSI-C library
- ▶ MAXIM Windows GUI



IPM-ADC

Analog to Digital IPack Module
16-bit A/D with 16 differential lines

Specifications

Input channels

- 16 differential or 32 single-ended

Switch-selectable input range

- $\pm 2.5V$, $\pm 5V$, $\pm 10V$, 0-2.5V, 0-5V, and 0-10V ranges

Software-programmable gain (per channel)

- 1X, 2X, 4X and 8X

Time Synchronization

- 32-bit Resolution: 1 microsecond, Accuracy: 1 microsecond
- IRIG-B AM, Digital and 1-PPS inputs

Input resistance

- 1 MOhms, typical

Resolution

- 16-bit

Sampling Rate

- One channel (max.): 250 KHz (4 μ s/conversion)
- 16 channels (differential): 15.6 KHz (64 μ s/16 ch)
- 32 channels (single-ended): 7.8 KHz (128 μ s/32 ch)

Input over-voltage protection

- With power ON: Vss -20V to Vpp 40V
- With power OFF: Vss -35V to Vpp 55V

IPack Module bus clock

- 32 MHz

Physical dimensions

- IndustryPack Standard - Single size
- 3.9" x 1.8" (9.906 cm x 4.572 cm)

Reliability MTBF (MIL-HDBK-217 FN2, 30 °C)

- 468 917 hours

Environmental

- Standard Operating Temperature: 0°C to 70°C
- Extended Operating Temperature: -40°C to 85°C
- Relative Humidity for operation: 0 to 95% (non-condensing)

Power consumption

- +5V: 233 mA max
- +12V: 10 mA max
- -12V: 10 mA max

Supported IndustryPACK Carrier Boards

The IPM-ADC is a standard IndustryPack (IPack) module that can be used with MAX Technologies' PCI, CPCI, VME and PXI intelligent carrier boards. The IPM-ADC module can also be used with MAX Technologies' MAXVME-6400 VME-64x dumb carrier board or third party carrier board that offers 32-Mhz IPack support.

Software

MAXIM	MAXIM is a powerful and easy-to-use test & measurement GUI application for Windows 2000/XP
Low level 'C' - API	The low level 'C' language API allows any C program to communicate directly with the IPM-ADC IPack module. The 'C' API may be used with the MAX Technologies IPack dumb carrier board such as the MAXVME-6400. Also the 'C' API can be compiled on many OS for various third-party carrier boards with little or no modification.
MX Foundation	MX-Foundation is a multi-protocol high-level API that take full advantage of the MAX Technologies' intelligent carrier boards. MX-Foundation is available for Windows and Linux.

Ordering Information

Part Number	Description
MAX-IP-200136	ADC IPack Module, 250 KHz, 16-bit resolution, 32-single / 16-differential lines, 2K FIFO, IRIG-B input

Additional options, configurations, extended temperature versions and accessories are available. Please contact us to inquire.

www.maxt.com

Corporate Headquarters

7005 Taschereau Boulevard, 3rd floor
Brossard (Quebec) Canada J4Z 1A7

Toll Free: (N. America) +1-800-361-1629

Direct: +1-450-443-3332 • Fax: +1-450-443-1618

MAX
technologies